


Low Earth Leakage Range

Current Ratings: 3,6,10,16,25,32,50,63,80, 120 AMPS.

Operating Voltage: Single Phase – 230V up to Three Phase – 480VA.C.





The u200 filter Range has been specifically designed to overcome EMC problems inherently caused by switched mode power supplies, in applications especially where size constraints and low earth leakage are an issue.

This new range of micro size filters has high attenuation factors and high current capabilities without having a large profile. Switched mode power supplies electronically switch high voltages and currents to improve efficiency and reduce losses in power conversion. This switching generates high levels of Radio Frequency Interference (RFI) and high energy surges, which can disturb or damage other electronics circuits.

The u200 series is a two-stage design in 2, 3 or 4 line formats, with excellent suppression characteristics particularly at low frequency where switch mode power supplies tend not to perform and require effective attenuation. They also have very low earth leakage, which give the added benefit of being able to be used in medical devices and applications.

The filter components are housed in compact chassis mounted, aluminum enclosures that allows side or base mounting, it is then encapsulated in a polyurethane potting compound to give excellent protection against shock and vibration. These combinations give a total range of over 50 filter applications.

TYPICAL APPLICATIONS

- Switched mode power supplies
- High current switch mode power supplies
- Thyristor driven equipment
- Air conditioners/Fan controllers
- Uninterruptible power supplies
- Pulse width modulation circuitsMedical devices and applications

TECHNICAL ADVANTAGES

- High current capability
- Micro size
- High common & differential mode insertion loss
- Improved mid frequency performance
- Insulated safety screw contacts
- Side or base mounting
- Optional input transient suppression to suit application

COMMERCIAL ADVANTAGES

- Assists compliance with the EMC directive
- State of the art technology ensures superior performance
- Competitively priced
- Compact size Reduced weight Cost effective component



STANDARDS

The u200 range of filters is built in accordance with the relevant BS, VDE, UL, CE & CSA safety standards.

All Total EMC Products Ltd filters & power supplies are designed to meet the latest requirements for Health and Safety, Particularly EN 60939-2-2005
The u200 range is specifically designed to assist AC input - DC Output industrial frequency converters to meet European Emission standards. E.g. EN55011, EN55014, EN55022, EN50081-2 and EN50081-1.

REGULATIONS

From the 15th of December 2004 all electrical/electronic apparatus - with few exceptions - sold or taken into service within the European Community must comply with the essential requirements of the EMC directive 2014/30/EU. Failure to do so is a criminal offence in the U.K.



Technical Specifications

Single Phase - Two Stage

Current	No of	Operating	Max AC Volt	Earth Leakage	Inductance	Storage Temp	Temp Rise @	Termination	Dimensions								
(Amps)	Lines	Voltage @ 50- 60Hz	Drop @ Full Load		Per Line (Typical) mH	Range	Full Load	Туре			С			F	G		1
3 6 10 13 20	2	230V	<1V/Line	470uA	9.8 8.2 2.76 2.52 1.84	-25 to +85°C	<40°C _	Fast-On	120	60	40	109	30	5.2	24	5.2	M4 x 15mm
30 50 80 110				4.7mA 10mA	1.7 0.7 0.92 0.74			Phoenix Contact	170	130	50 70	160 223	10	30 65	36 50	5.2	M6 x 20mm


M = Earth Leakage up to 300uA S = Earth Leakage below 100uA

Three Phase - Two Stage


Current No of Operating Max AC Volt Earth Inductance Storage Temp Rise @ Termination										Dimensions									
(Amps)	Lines		Drop @ Full Load	Leakage	Per Line (Typical) mH	Temp Range	Full Load	Type	A	В	С	D	E	F	G	н	1		
3 6 10		230V – 440V 440V		470uA	4.4 2.4 1.4	-25 to +85°C	<40°C	Fast-On	120	60	40	109	30	5.2	24	5.2	M4 x 15mm		
32				5mA				Phoenix	230	130	70	223	20	65	50		M6 X 20		
Current	No of	Operating	Max AC Volt	Earth	Inductance	Storage	Temp Rise @	Termination	Dimensions										
(Amps)	Lines	Voltage @ 50-60Hz	Drop @ Full Load	Leakage	Per Line (Typical) mH	Temp Range	Full Load	Туре	A	В	С	D	E	F	G	н	_		
3					4.4														
10	4	230V – 440V	<1V/Line	470uA	1.4	-25 to +85°C	<40°C	Fast-On	120	60	40	109	30	5.2	24	5.2	M4 x 15mm		
13					1.2														
32		440V		5mA				Pheonix	230	130	70	223	20	65	50		M6 X 20		

Dimensional Data


3,6,10,13,20 Amp 2 Line 3,6,10,13 Amp 3/4 Line



30,50 Amp 3 Line




80,110 Amp 3 Line






Schematics


Single Phase




Two Phase




Three Phase





Three Phase & Neutral



Performance characteristics insertion loss curves







Performance will deteriorate with higher current ratings. Curves given are average readings.

Part number / Ordering information

U200/***/*/2/*

U200 = Range of filter

* = No of Lines on filter (2,3,4)

* = Options (listed below)

*** = Amp Rating of filter

2 = No of Stages on filter

Options (noted belot

Options:

T = Transient, E = Earth Line Choke, H = High Performance, M = Medical up to 300uA, S = Medical below 100uA, - = neither (no options)

In addition to the standard range of filters & power supplies, Total EMC Products specialize in the design and manufacture of filters to suit your specific requirements.

Due to continuous development Total EMC Products Ltd reserve the right to amend any information contained within this datasheet without prior notice.

@ 10/2012 Total EMC Products Ltd. E & OE The contents of the datasheet must not be copied by any means without prior written agreement.